


Create Groups to Broadcast Commands to Multiple Devices

The Device Groups page is used to group multiple devices into specific groups that will allow personnel to send one broadcast command or data request to all devices. For example, an operator may want to have all devices report in with a maintenance report — create one group and send one command.



Navigate to the Device Groups page

- 1 At the left navigation menu, select Device Groups.

Tidbit

If a group has been created, a table will be shown

All groups need to be the same model type e.g. T646

Verify a device received the command by going to its history page

After a command is broadcasted, wait until all devices have reported in before sending a command to an individual device

Create New Group		
Group	Model	Option
Cooper Form 4C Reclosers	T646	Modify Group Request Status Send Command Delete Group
SEL351 Reclosers	DNP-RTM	Modify Group Request Status Send Command Delete Group
End of Line Meters	TVM 1/3	Modify Group Request Status Send Command Delete Group
Capacitor Controls	TC012	Modify Group Request Status Send Command Delete Group
All T422 Units	T422	Modify Group Request Status Send Command Delete Group

Group is the group name that has been created by a user that describes the function or related equipment. For example, Cooper Form 4C Reclosers describes the equipment the group controls.

Model is the product family that represents the devices in the group. For example, all devices in the Cooper Form 4C Reclosers group are T646 units. This is automatically created when the group is created and devices are assigned.

Options are the available actions that can be perform on the group: [Modify Group](#), [Request Status](#), [Send Command](#), [Delete Group](#)

Create a Group

- 1 At the top of the menu, select **Create New Group**.
you will see the Create Groups page and a pull-down menu listing product families: Model T6XX, Model TVM 1/3, Display Only Group, DNP-RTM, Profile
- 2 Scroll down the menu and select the product family.
- 3 Once the product family is selected, select the Press to Continue button.

Device Groups

Broadcast Commands

you will see the Create Device Groups page, a field for the group name, and devices that can be assigned to the group

- 4 In the Group Name field, enter a group name to describe the function or related equipment.
- 5 Locate the desired device and **check** the box to **add** or **uncheck** to **remove**.
- 6 Select the Save Changes button and Press to Continue button after the Save Groups prompt.

Add or Remove a Device within a Group

- 1 In the Options column, select **Modify Group**.

you will see the Maintain Device Groups page, a field for the group name, and all devices that are both assigned and de-assigned within the group

- 2 Locate the desired device and **check** the box to **add** or **uncheck** to **remove**.
- 3 Select the Save Changes button and Press to Continue button after the Save Groups prompt.

Request a Report from all Devices within a Group

- 1 In the Options column, select **Request Status**.

you will see the Device Group:devices page and a pull-down menu with a listing of reports

- 2 At the pull-down menu, select the desired report.
- 3 After the selected report is highlighted, press the Request Report button to broadcast the request to all devices.

*you will see **The Report has been requested** which verifies the request was broadcasted*

- 4 After the request is broadcasted, select the Press to Continue button to return to Device Groups.

Send a Command to all Devices within a Group

- 1 In the Options column, select **Send Command**.

*you will see the Device Group:devices page and two pull-down menus: a list of available commands and a choice for permanently or **momentarily opening / closing an output**.*

*Select **momentary** when you want the output to toggle.*

- 2 At the pull-down menu, select the command to be broadcasted.
- 3 After the selected command is highlighted, press the Send Command button to broadcast the command to all devices.

*you will see the Device Group:devices page and a prompt **The Command has been requested**.*

- 4 After the command is broadcasted, select the Press to Continue button to return to Device Groups.

Delete a Group

- 1 In the Options column, select **Delete Group**.

*you will see the Delete Group Confirmation page and will be prompted **Are you sure you want to delete group: <group name>** - two action buttons are displayed **Continue** and **Cancel**.*

- 2 To delete the group, select the Continue button.

*you will see the Delete Groups page and the prompt **The group has been deleted***

- 3 To complete the action, select the Press to Continue button.